

marantz®

SR4320 Stereo Receiver

A full-featured stereo control center that combines exceptional sound quality with a host of performance and convenience features including remote control operation. The SR4320 provides seven audio inputs including phono to accommodate a variety of music sources, and features a fully discrete amplifier section for clear and powerful sonic performance. This enables it to form the core of a stand alone hi-fi system, but also to be added in to high quality Multi-zone installations.

- 80 Watts x 2 - Discrete Amplifier Stages
- Oversized Power Transformer
- Heavy Duty Speaker Terminals
- Preamp Outputs/Main-amp Inputs (for the addition of a More Powerful Amplifier - Perfect for Whole House Audio Distribution Systems)
- Video Inputs for DSS, VCR and DVD
- Video Output for VCR and Monitor
- Speaker Outputs: - A, B, A+B, OFF
- D-BUS (RC-5 In/Out) Remote Connection
- Full Function Remote Control



FEATURES		SPECIFICATIONS	
Number of Channels	2	AUDIO SECTION	
Discrete Amplifier Stage	•	Power Output (8 ohms)	80W x2
Power Transformer	EI	Frequency Response (+/- 3 dB)	20Hz - 20kHz
Speaker A/B	•	THD (20Hz - 20kHz, 8 ohms)	< 0.08%
Tone Control (Bass/Treble)	•	S/N Ratio	95 dB
Preset Station Memory	30	TUNER SECTION FM	
Chassis	Metal	Frequency Range	87.5 - 108.0MHz
IN/OUTPUTS		S/N Ratio (Mono/Stereo)	70/65 dB
AUDIO		Distortion (Mono/Stereo)	0.2/0.3 %
Analog L&R In	7	Stereo Separation	40 dB (1kHz)
Analog L&R Out	3	TUNER SECTION AM	
Pre-Amplifier Out	•	Frequency Range	520 - 1710kHz
Main Amplifier In	•	Usable Sensitivity	Loop 400_V
Phono In	•	S/N Ratio	50 dB
Headphone Out	•	GENERAL	
VIDEO		Color	Black
Composite In	3	Front Panel	Brushed Plastic
Composite Out	2	Remote Control	Device Remote RC4320SR
OTHER		Power Requirements	AC 120 V, 60Hz
D-Bus Remote (RC-5) In/Out	1/1	Power Consumption	220 W
AC Outlets (Switched/Unswitched)	1/1	Dimension W x H x D (Inches)	17 1/2" x 6 1/2" x 14 1/2"
		Weight (lbs.)	18.5

*All specifications, dimensions and weights are subject to change without notice. D&M Holdings, Marantz, Marantz America, Inc. or any of its subsidiaries will not assume any liability for errors within this document.